

מגבר קיר ביתי Polman PLM837

ה PLM 837 הוא מגבר קומפקטי המספק מרכז בקרת מוזיקה ביתי נוח ויעיל למשתמש. הוא מגיע בצבעים שונים לבחירה עם עיצוב מראה יוקרתי ומינימלסטי שמשתלב בצורה אלגנטי על הקיר.

יש לו מקורות שמע מגוונים ונוחים כמו FM, SD, BT, USB, AUX1, AUX2 ומספק הפעלה נוחה ומהירה.

יציאות הרמקולים הן ב-8 אום ותגובת התדר היא 20Hz-20kHz. הוא תומך בשלט רחוק אינפרא אדום, ויש לו מסך LED מואר לנוחות תפעול.

תוכלו לראות את השעה, הכותרת ומספר השירים הכוללים על המסך. בנוסף אפשרות שליטה על עוצמת הקול, מצב העבודה על ידי לחצנים ושלט רחוק.

ה PLM 835 יתאים מאוד לבתים פרטיים מסעדות, חנויות, משרדים ועוד...

נתונים עיקריים:

- קופסא 86 סטנדרטית
- עיצוב מראה יוקרתי עם מסך LED
- מגבר מובנה בעוצמה של 2x10W @ 8Ω
- קישוריות Bluetooth
- כניסת USB, Micro SD ו 2 ,FM-כניסותAUX
- תמיכה בשלט רחוק
- יכול לאחסן 20 ערוצי רדיו כולל תמיכה בחיפוש אוטומטי וידני
- תגובה 20Hz ~ 20kHz
- תמיכה ב MP3, WMA, WAV, FLAC-ועוד.

מפרט טכני:

Power input	~100~240V
Output power	2×10W
Rated impedance	8Ω
Total harmonic distortion	±0. 03% (1KHz, 1W, 8Ω)
Signal- to- noise ratio	>81dB
Frequency response	20Hz~20kHz
Sensiti vity of auxil iar y input	AUX1: 1V/50 0mV
(a djust able)	AUX2: 1V/50 0mV
Audi o f ormat	MP3, WMA, WAV, FLAC, etc.
Bluetooth	BT2.1+EDR
Storage type	Suppor t TF card wi th a maximum capacity not exceeding 32GB
Prod uct dimension	86×86×38mm
Included angle of effective emitter region	60°
Effective remote -controlled distance	8- 12m
Battery of remote controller	CR2032